Model: Note Pickup shape is just for reference. PRS Paul's Guitar All pickups using this diagram PRS Custom 24-08 shall be oriented in this manner. PRS S2 Custom 24-08 Bass (Neck) Pickup Solder bass pickup $0 \circ 0 \circ 0 \circ 0 \circ 0$ harness shielding North Pickup Bridge to pot casing Cavity Ground Solder both Ground South Wire pickups' harness $\ominus \circ \ominus \quad \ominus \quad \ominus \quad \ominus \circ \ominus$ Wires shielding and pickup cavity grounds together Volume Solder shielding from jack wire . \bigcirc to pot casing 180 pF Treble (Bridge) Pickup .033 uF $0 \circ 0$ 0 0 0 South То North $\ominus \circ \ominus \ \ominus \ \ominus \ \ominus \circ \ominus$ Tone Output Jack Mini Toggle Switches: Bridge location Treble Bass Pickup Pickup Side Side **Bass Pickup Wires Treble Pickup Wires** E - Green A - Green B - Red F - Red FH C - White G - Dearborn D - Dearborn H - Black 3-way Pickup Selector Switch: **Operating Instructions** 3-Way Toggle Switch Position 1 (down) - Treble Pickup D Position 2 (middle) - Treble and Bass Pickups Position 3 (up) - Bass Pickup Mini-Toggle Switches Down - Humbucker Mode Up - Single Coil Mode

